

## S345C

### SPECIFICATION

- **Core Logic**  
Intel GM45/ICH9M
- **Processor**  
Support Socket P, FSB 667/800/1066MHZ  
Support Intel Mobil CPU Celeron M 575, T3100 ;  
Core2Duo P8400 & P8600 CPU
- **Memory**  
Support SODIMM, DDR III 800/1066MHz \*2; Memory size up to 8GB
- **Graphics**  
Integrated Intel Graphics Media Accelerator 4500MHD
- **Audio**  
High definition audio CODEC
- **LAN**  
Built-in Intel 10/100/1000Mbps Ethernet controller
- **Storage Devices**  
Support 2.5" SATA hard disk drive & SSD
- **Hardware Monitor**  
CPU temperature, cooling fan speed, system voltage
- **Power Management**  
ACPI 3.0 compliance OS direct power management; Wake-on event
- **IO Ports and Switch**

#### Front Panel:

1 x RS232(COM) port  
1 x USB 3.0 port(do not support booting feature);  
1 x MIC phone jack;  
Power-on button;

4 x USB 2.0/1.1 ports  
1 x Ear phone jack  
Power/HDD LED

#### Back Panel:

1 x DVI-I port (Supports VGA and TV-out function);  
1 x Express card/34 slot;  
2 x PS/2 ports for Keyboard & Mouse  
1 x USB 3.0 port(do not support booting feature);  
1 x DC 10~26V Power-in connector

1 x DVI-D port  
1 x RJ45 10/100/1000Mb LAN port

1 x USB 2.0 / 1.1 port

#### Internal:

1 x mini card slot (Supports Mini PCIe and USB devices)

- **Dimension & Volume**  
102(W) x 148(D) x 38(H) mm; 0.58 Liter
- **AC Adapter**  
NA / 10V ~ 26V DC power input
- **Accessories**  
Power Adaptor, DVI/VGA converter; DVI-D converter; Driver CD, User's Guide,  
CPU Cooler, Car PC Power Wire, Screws Pack

