

S385G3

- **Processor**
Onboard Intel Celeron 2980U 1.6GHz or i3-4010U 1.7GHz, integrated 8 series chipset
- **Memory**
2 sockets, SODIMM DDR3 up to 1600MT/s and 16GByte
- **Graphics**
Integrated Intel HD graphics in processor (Haswell-ULT)
- **Audio**
Realtek ALC892 high definition audio CODEC
- **LAN**
Built-in Intel i218LM 100/1000Mbps Intel Ethernet
Three Intel i210-AT Ethernet controllers
- **Storage Devices**
Supports SATA 6Gb/s and 3Gb/s specification
Supports 2.5" SATA hard disk drive and solid state drive
- **BIOS & Hardware Monitor**
Insyde UEFI BIOS
CPU temperature, cooling fan speed, system voltage
- **Switches and Connecting Ports**
 - Front Plate:**
 - 3 x USB 2.0
 - 1 x MIC
 - 1 x Line out
 - 2 x RS232
 - 4 x RJ45 100/1000Mb Fast Ethernet
 - Power-on button
 - Power and HDD LED
 - Back Plate:**
 - 1 x DVI-D (VGA monitor is not supported)
 - 1 x DP (Display Port)
 - 2 x PS/2 for Keyboard and Mouse
 - 2 x USB 3.0 Ports
 - 1 x DC 12V Power-in Jack
 - Internal:**
 - 1 x mini PCIe slot supports PCIe mini card or miniSATA
- **Dimension & Volume**
102(W) x 148(D) x 38(H) mm; 0.58 Liter
- **AC Adaptor**
Universal 100~240V AC in/12V 60W DC Power Adapter
- **Accessories**
Power Adaptor, Driver DVD, User's Guide, CPU Cooler, Screws Pack

